

JISフランジ(BL)YKバルンサー選定表

呼び径	2K	5K	10K	16K	20K
100A	×	×	×	×	×
				(6.29)	(6.61)
125A	×	×	×	SR-10	SR-10
		(5.16)	(7.18)	(9.21)	(10.5)
150A	×	×	SR-10	SR-10	SR-10
		(7.47)	(10.1)	(12.7)	(14.4)
175A	×	SR-10	SR3-20	-	-
		(9.52)	(11.8)		
200A	×	SR3-20	SR3-20	SR3-20	SR3-20
		(12.1)	(13.9)	(18.4)	(20.8)
225A	×	SR3-20	SR3-20	-	-
		(13.9)	(15.8)		
250A	×	SR3-20	SR3-20	SR3-45	SR3-45
		(19.2)	(22.6)	(30.4)	(36.2)
300A	×	SR3-45	SR3-45	SR3-45	SR2-60
		(24.2)	(27.8)	(40.5)	(47.4)
350A	×	SR3-45	SR3-45	SR2-60	SR-75
		(33.0)	(36.9)	(57.5)	(66.1)
400A	×	SR3-45	SR2-60	SR-75	SR2-90
		(41.7)	(52.1)	(81.7)	(97.0)
450A	SR2-60	SR2-60	SR-75	SR2-90	SR-110
	(48.8)	(52.7)	(68.4)	(107.0)	(126.0)
500A	SR-75	SR-75	SR-75	SR-110	×
	(57.1)	(61.6)	(81.6)	(132.0)	(155.0)
550A	SR-75	SR-75	SR2-90	×	×
	(75.2)	(80.8)	(105.0)	(163.0)	
600A	SR2-90	SR2-90	SR-110	×	×
	(86.3)	(92.7)	(120.0)		
650A	SR2-90	SR-110	×	×	×
	(99.1)	(106.0)	(144.0)		
700A	SR-110	SR-110	×	×	×
	(111.8)	(120.0)			
750A	SR-110	×	×	×	×
	(130.3)	(150.0)			
800A	×	×	×	×	×
	(144.7)				

()は蓋の近似計算質量(参考)(kg)